

IC-G88

VHF TRANSCEIVER

1500 mW Powerful Audio, Waterproof and User-Friendly Operation to Match Various Needs





1 2ABC 3 DEF 4 GHI 5 JKL 6MNO 7PORS 8TUV 9WXYZ





SPECIFICATIONS

GENERAL	IC-G88		
Frequency coverage	136–174 MHz		
Type of emissions	16K0F3E, 11K0F3E (25/12.5 kHz)		
Number of channels	128 channels		
Antenna impedance	50 Ω (BNC)		
Power supply requirement	7.5 V DC		
Operating temperature range	-30 °C to +60 °C (Radio only)		
Frequency stability	±2.5 ppm		
Current drain (Approximate)			
Tx High	1.5 A		
Rx Maximum audio/Stand-by	500 mA (Internal SP) / 77 mA		
Dimensions (W×H×D)	52.2 × 111.8 × 30.3 mm (with BP-280)		
(Projections not included)	32.2 × 111.0 × 30.3 mm (with Br-200)		
Weight (Approximate)	270 g (with BP-280)		
TRANSMITTER			
Output power (at 7.5 V DC)	5.5/ 2.0/ 1.0 W (Hi/L2/L1)		
Maximum frequency deviation	±5.0 kHz/±2.5 kHz (Wide/Narrow)		
Spurious emissions	70 dB minimum		
External microphone connector	3-conductor 2.5 (d)mm (¹ / ₁₀ ")/2.2 kΩ		
RECEIVER			
Sensitivity	0.25 μV typical (at 12 dB SINAD)		
Squelch sensitivity	0.25 µV typical (at threshold)		
Adjacent channel selectivity	76 dB/ 53 dB typical (W/N)		
Intermodulation	74 dB typical		
Spurious response	70 dB minimum		
Audio output power			
Internal speaker	1500 mW typical (8 Ω load)		
External speaker	400 mW typical (8 Ω load)		
External speaker connector	3-conductor 3.5 (d) mm (1/8")/ 8 Ω		
Measurements made in accorda	ance with FIA/TIA-603		

All stated specifications are subject to change without notice or obligation.

Applicable U.S. Military Specifications & IP Rating

Standard	MIL 810G				
Standard	Method	Procedure			
Low Pressure	500.5	I, II			
High Temperature	501.5	I, II			
Low Temperature	502.5	I, II			
Temperature Shock	503.5	I-C			
Solar Radiation	505.5	I			
Rain Blowing/Drip	506.5	I, III			
Humidity	507.5	II			
Salt Fog	509.5	_			
Dust Blowing	510.5	I			
Immersion	512.5	I			
Vibration	514.6	I			
Shock	516.6	I, IV			
Also resets a minute state ANII OTD 040 O. D. E and E					

Also meets equivalent MIL-STD-810-C, -D, -E and -F.

Ingress Protection Standard				
	IP67 (Dust-tight and waterproof protection)			

Supplied accessories: (May differ, depending on version)

 Battery pack, BP-280 Desktop charger, BC-213 AC adapter, BC-123SA/SE

 Belt clip, MB-133 • Antenna, FA-B2E

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details



Battery packs	Туре	Capacity	Operating time*
BP-278	Rechargeable	1130 mAh (min.)	Up to
DF-276	Li-ion	1190 mAh (typ.)	10 hours
BP-279	Rechargeable	1485 mAh (min.)	Up to
DF-2/9	Li-ion	1570 mAh (typ.)	14 hours
BP-280	Rechargeable	2280 mAh (min.)	Up to
	Li-ion	2400 mAh (typ.)	20 hours

*Tx: Rx: standby = 5:5:90. Power save function ON.



Charges the BP-280 in 3.5 hours



For use with For use with the BC-213 the BC-214


CIGARETTE LIGHTER CABLE &

POWER SUPPLY CABLE

*1 BC-123SA for the USA plug, SE for the European plug, SV for the Australian plug









*2 Either the VS-4LA or OPC-2004LA is required when using the HS-97.







FA-B2E VHF ANTENNA Same as supplied.

AD-130 CHARGER ADAPTER

AD-130 charger adapter is supplied with the BC-214.



The "3D GENUINE Icom label" is attached for proof of authentication. Check the Icom website for details: http://www.icom.co.jp/world/genuine-info/

Icom, Icom Inc. and the Icom Iogo are registered trademarks of Icom Incorporated (Japan) in Japan, the United States, the United Kingdom, Germany, France, Spain, Russia, Australia, New Zealand and/ or other countries. All trademarks are the properties of their respective holders.

ICOM INC. 1-1-32, Kamiminami, Hirano-Ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

www.icom.co.jp/world

Count on us!

Icom America Inc. www.icomamerica.com

Icom Canada www.icomcanada.com

Icom Brazil

E-mail: sales@icombrazil.com

Icom (Europe) GmbH www.icomeurope.com

Icom Spain S.L. www.icomspain.com

Icom (UK) Ltd. www.icomuk.co.uk

Icom France s.a.s. www.icom-france.com

Icom (Australia) Pty. Ltd. www.icom.net.au

Shanghai Icom Ltd. www.bjicom.com

Your local distributor/dealer: